

PSEN cs6.1p/PSEN cs6.1 1unit

542100



RFID safety switch 2 safe semiconductor outputs, 8-pin M8 connector, IP67, 4 directions of actuation, Operating distance (direction of actuation square): 11 mm, Sao = 8 mm, Sar = 20 mm, PU = 1 piece fully coded switch with actuator A total of 8 learning procedures are possible.

Technical details

Certifications:	CE;cULus Listed;EAC (Eurasian);TÜV;FCC;IC;ECOLAB
Sensor principle:	Transponder
Type of coding:	Fully coded
Number of OSSD outputs:	2
Number of inputs:	2
Connection type:	M8, 8pol. male
Supply voltage (V):	24,0
Supply voltage type:	DC
Power consumption DC:	1.0 W
Protection type, housing:	IP66;IP67
Coding level EN ISO 14119 aligned:	hoch
Product Material:	PA+GF;PBT;Polycarbonat
Pollution degree:	3
Tolerance of supply voltage:	-20 %/+20 %
Overvoltage category:	III
Width dimension:	97.6 mm
Height dimension:	26.4 mm
Depth dimension:	13.0 mm
Gross weight:	75 g
Net weight:	58 g

Ambient temperature:

-25 - 70 °C

Optional accessories



532110

PSEN Winkel / bracket



533150

PSEN cable M8-8sf, 2m



533151

PSEN cable M8-8sf, 5m



533152

PSEN cable M8-8sf, 10m



533153

PSEN cable M8-8sf, 20m



533154

PSEN cable M8-8sf, 30m



533155

PSEN cable M8-8sf M8-sm, 0.5m



533156

PSEN cable M8-8sf M8-8sm, 1m




533157

PSEN cable M8-8sf M8-8sm, 2m




540329

PSEN converter M8-8sf -- M12-8sm



540310

PSEN screw M4x16 10pcs



540309

PSEN screw M4x12 10pcs



540130

SDD ES ETH



540132

SDD ES PROFIBUS



532109

PSEN cs bracket stop sliding door



532111

PSEN mag/cs bracket straight



535111

PSEN ix2 F4 code



540317

PSEN Y junction M8 SENSOR



540318

PSEN Y junction M8 cable channel



540337

PSEN Y junction M8-M12/M12 PIGTAIL



535112

PSEN ix2 F8 code



532108

PSEN cs bracket stop swinging door
